

Univox® IR 1211

Infrared Emitter (extender to IR 1411)

Features

- 2 Watt infrared emitter with integrated modulator
- Selectable 2.3 and 2.8 MHz carrier frequencies
- 730 m² coverage range (free field)
- 2 mono channels or 1 stereo
- 72 high efficiency diodes for maximum coverage
- Convection cooled
- Automatic gain control
- BNC modulated audio input and parallelled output to daisy-chain signal
- · Wall/ceiling mount included
- 1/4 inch female mounting thread top and bottom

High Performing Assistive Listening

Univox® IR1211 is a compact yet powerful IR emitter for small to medium size venues. IR1211 works as an extender to the IR1411 main unit.

The powerful infrared emitter features 72-diodes emitter for high performance and large coverage – up to 730 m². Univox® IR1211 provides wireless assistive listening with high audio quality. With two mono channels or single channel stereo operation on 2.3 and 2.8 MHz carrier frequencies, the unit is ideal for applications where information security and overspill control are of importance.

Emitter units can be daisy chained through the "RF out" jacks on the primary, and the "RF In" jack on the secondary units by using BNC cables. Each secondary unit must be powered by 24VDC power supply. Once the units are connected and powered no additional settings needed.





Copyright ©

Univox® IR 1211 Emitter

Technical data

Modulation FM

IR Light Wavelength 870 nm

 $\begin{tabular}{ll} \begin{tabular}{ll} \be$

Input connectionBNC 50 ΩOutput connectionBNC 50 ΩThreshold for auto on/off50 mVSupply voltage (nominal)24 VDCSupply voltage (minimum)19 VDCSupply voltage (maximum)28 VDCLED qty72

Optical power > 1.5 W

Range Up to approximately 730 m² (free field)

Power Supply Input 100-240 VAC 50/60 Hz


Power Supply Output 24 VDC @ 2 A


Power Connection 2.5 mm DC jack (or 4-Pin Phoenix connector)

Power Supply Wattage 48 W Weight 450 g

Dimensions (W) 210 x (D) 70 x (H) 80 mm (8.3" x 2.8" x 3.1")

Color Black
Part no 650302







-1211-br-gb 2022-03-28 Copyright © Bo Edin AB

For complete manual, please refer to univox.eu.

Stockby Hantverksby 3, S-181 75 Lidingö, Sweden